

## SMA Male to N Male Adapter



# **RF Adapters Technical Data Sheet**

**PE9080** 

## Configuration

- SMA Male Connector 1
- N Male Connector 2

#### **Features**

- Max VSWR of 1.3:1 up to 11 GHz
- SMA and N Interface compliant with MIL-STD-348A
- 50 Ohms
- · Straight Body Geometry
- · Gold Plated Brass Contact
- 50 μ-in min. Gold Contact Plating

## **Applications**

Allows Connection Between Series

General Purpose Test

#### Description

Pasternack's PE9080 SMA male to type N male adapter is part of our full line of RF components available for same-day shipping. The SMA connector mates mechanically with commercially available 3.5mm and 2.92mm (K) connectors. Our SMA to type N adapter has a male to male gender configuration. PE9080 SMA male to type N male adapter operates to 11 GHz. The Pasternack RF adapter provides good VSWR of 1.3:1 maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		11	GHz
VSWR			1.3:1	
Operating Voltage (AC)			500	Vrms

### **Mechanical Specifications**

Size

 Length
 1.28 in [32.51 mm]

 Width
 0.787 in [19.99 mm]

 Weight
 0.074 lbs [33.57 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Male to N Male Adapter PE9080

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



## SMA Male to N Male Adapter



# **RF Adapters Technical Data Sheet**

**PE9080** 

Connector 1	Connector 2	
SMA Male	N Male	
Standard	Standard	
MIL-STD-348A	MIL-STD-348A	
5/16 in		
3 to 5 in-lbs [0.34 to 0.57 Nm]		
	SMA Male Standard MIL-STD-348A 5/16 in	

### **Material Specifications**

	Connector 1		Connector 2		
Description	Material	Plating	Material	Plating	
Туре	SMA Male		N Male		
Contact	Brass	Gold	Brass	Gold	
		50μ in. minimum		50μ in. minimum	
Insulation	PTFE		PTFE		
Body	Brass	Nickel	Brass	Nickel	
		100μ in. minimum		100μ in. minimum	
Gasket	Silicone		Silicone		
Coupling Nut	Brass	Nickel	Brass	Nickel	
		100μ in. minimum		100µ in. minimum	

# **Environmental Specifications Temperature**

Operating Range

-65 to +165 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Male to N Male Adapter PE9080

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451



## SMA Male to N Male Adapter



## **RF Adapters Technical Data Sheet**

**PE9080** 

SMA Male to N Male Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Male to N Male Adapter PE9080

URL: https://www.pasternack.com/sma-male-n-male-straight-adapter-pe9080-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

# PE9080 CAD Drawing

SMA Male to N Male Adapter

