

## 75 Ohm N Female to F Male Adapter



# **RF Adapters Technical Data Sheet**

PE9739

## Configuration

- N Female Connector 1
- F Male Connector 2

- 75 Ohms
- Straight Body Geometry

#### **Features**

Max VSWR of 1.3:1 up to 3 GHz

## **Applications**

• Allows Connection Between Series

General Purpose Test

#### Description

Pasternack's PE9739 75 ohm type N female to type F male adapter is part of our full line of RF components available for same-day shipping. Our type N to type F adapter has a female to male gender configuration. PE9739 type N female to type F male adapter operates to 3 GHz. The Pasternack RF adapter provides good VSWR of 1.3:1 maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/ disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		3	GHz
VSWR			1.3:1	

#### Performance by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency Range	DC to 2	2 to 3				GHz
VSWR, Max	1.15:1	1.3:1				

### **Mechanical Specifications**

Size

 Length
 1.75 in [44.45 mm]

 Width
 0.625 in [15.88 mm]

 Weight
 0.086 lbs [39.01 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 75 Ohm N Female to F Male Adapter PE9739

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



# 75 Ohm N Female to F Male Adapter



# **RF Adapters Technical Data Sheet**

**PE9739** 

Description	Connector 1	Connector 2
Туре	N Female	F Male
Polarity	Standard	Standard
Hex Size		7/16 in.

#### **Material Specifications**

	Conn	ector 1	Conne	ector 2
Description	Material	Plating	Material	Plating
Туре	N Female		F Male	
Contact	Beryllium Copper	Gold		Nickel
Outer Conductor Pa	assivated Stainless Stee			
Body			Brass	Nickel

## **Environmental Specifications**

**Temperature** 

Operating Range -65 to +125 deg C

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

75 Ohm N Female to F Male Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 75 Ohm N Female to F Male Adapter PE9739

URL: https://www.pasternack.com/n-female-f-male-straight-adapter-pe9739-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

# PE9739 CAD Drawing

75 Ohm N Female to F Male Adapter

